

Q2400 SERIJA U TIHOJ KUTIJI



Generator

MODEL	18CM50	20CM50	24CT50
Mecc Alte Generator	Monofazni 50 Hz 1PF 1500 rpm	Monofazni 50 Hz 1PF 1500 rpm	Trofazni 50 Hz 0,8PF 1500 rpm
Snaga LTP**	18.0	19.9	24.1
Snaga PRP*	17.1	19.0	23.3
Napon	230	230	230/400
Snaga u amp. PRP*	74.3	82.6	33.6
Potrošnja goriva	5.8	5.8	5.8

Motor

Baza	Kubota
Konfiguracija	4 cilindra u liniji - 4 taktni dizel
Regulacija	Mehanički
Zapremnina	2.434 l [148.5 in3]

Dimenzije i težina

Q2400 u tihoj kutiji	18CM50	20CM50	24CT50
Dužina mm [in]	1300 [51.1]	1300 [51.1]	1300 [51.1]
Širina mm [in]	600 [23.6]	600 [23.6]	600 [23.6]
Visina mm [in]	695 [27.3]	695 [27.3]	695 [27.3]
Težina Kg [lbs]	436 [961]	436 [961]	436 [961]

* PRP = Primarna snaga.

**LTP = Konstantna snaga.

Napomena : Slike su simbolične.

Q2400 SERIJA U TIHOJ KUTIJI



Generator

MODEL	20CM60	23CM60	28CT60
Mecc Alte Generator	Monofazni 60 Hz 1PF 1800 rpm	Monofazni 60 Hz 1PF 1800 rpm	Trofazni 60 Hz 0,8PF 1800 rpm
Snaga LTP**	19.6	22.9 KW	27.8 KVA
Snaga PRP*	21.3	21.8 KW	26.6 KVA
Napon	2x120	2x120	208
Snaga u amp. PRP*	81.7	90.8	73.8
Potrošnja goriva	6.6	6.6	6.6

Motor

Baza	Kubota
Konfiguracija	4 cilindra u liniji - 4 taktni dizel
Regulacija	Mehanički
Zapremnina	2.4 l [148.5 in3]

Dimenzija i težina

Q2400 u tihoj kutiji	20CM60	23CM60	28CT60
Dužina mm [in]	1300 [51.1]	1300 [51.1]	1300 [51.1]
Širina mm [in]	600 [23.6]	600 [23.6]	600 [23.6]
Visina mm [in]	695 [27.3]	695 [27.3]	695 [27.3]
Težina Kg [lbs]	436 [961]	436 [961]	436 [961]

* PRP = Primarna snaga.

**LTP = Konstantna snaga.

Napomena : Slike su simbolične.